

# Tblitz Dots Wireless

## **Resetting**

the Headphones Remove the headphones from the docking station and turn them off. Then press both multifunction buttons simultaneously for 15-20 seconds or until they flash red and blue. Put the headphones back in the dock, delete the pairing record from the mobile device, and pair again.

## **Charging the charging case**

Connect the case to the charger via the USB - micro USB connector on its side.

## **Headphones:**

Insert the headphones into the power supply case, the red LED indicates the discharged headphones.

## **Power supply case:**

The LED lights up blue during charging.  
When fully charged, all diodes go out.

## **Switching on the headphones**

Open the case door and remove the headphones, this will switch on automatically. If the headphones are out of the case and are switched off, press the button for 3 seconds or until the red and blue LEDs flash alternately.

## **Switching off the headphones**

If you insert the headphones into the charging case, they will switch off automatically. To turn off the headphones outside the case, hold down the button for 5 seconds.

## **Switch the headset on again**

When the pairing is successful, the headset switches to automatic connection to the mobile device the second time it is switched on.

## **To connect headphones to the device**

1. Remove the headphones and hold both multifunction buttons for 3 seconds to turn on until the LED flashes red and blue alternately.

Pair the main handset (right), the LED flashes red and blue alternately. The other handset glows slowly and the handsets are paired.

2. Turn on Bluetooth in your phone. If you have Android, go to settings and click "search for devices." If you have iOS, the system will automatically start searching for new devices. When you find the headset on your phone, click pairing. If the pairing is successful, the right handset will prompt for successful pairing, the left handset will flash blue slowly. After successful pairing, the right handset is the main channel, the left handset is the secondary.
3. The headset can be paired with the mobile phone separately. The operating method can be performed according to step 2 above.

Each time you use the headset again, it automatically pairs with your phone when you remove it from the docking station.

## **Function:**

### **Play / Pause**

When the headphones are in standby mode, press the multifunction buttons to start playback. To stop playback, press the multifunction buttons.

### **Switching tracks / volume control / activating Siri**

While playing music, press the multifunction button three times to switch tracks. To control the volume, press the button twice. To activate Siri, press the button for 2 seconds.

### **Answering calls**

Press the key to answer the call.

### **Ending calls**

Press the end key.

### **Rejecting a call**

Press the button for 2 seconds to reject the call.

### **Battery Prompt**

When the headphones are exhausted, a low battery tone sounds every 30 seconds until the headphones turn off.

### **Safety Information**

1. Charge in a safe environment. Once the power case is charged, remove the USB cable to prevent damage to the case.
2. When listening to music, adjust the volume to a suitable level to avoid damaging your hearing.
3. Try to avoid using the headphones in a location with source interference, otherwise the headphones may be affected.
4. Try to avoid using the headphones in a corrosive environment to avoid affecting functionality.

### **Tips & Warnings**

When using headphones to listen to music or make calls, pay attention to the correct settings to avoid damaging your hearing at excessive volume!

### **Restrictions on use**

- Do not expose the headphones to direct fire or water (showering, swimming, etc.).
- Avoid using the product in a dusty, dirty environment. Do not expose the device to magnetic fields. Failure to do so may damage the circuits inside the device.
- Use and store the device at temperatures between -10 ° C and 55 ° C. • Extreme heat or cold can damage the device. At temperatures below 5 ° C, battery life will deteriorate.
- Do not expose the device to direct sunlight, such as car dashboards or window sills.
- Do not place the device near devices with strong magnetic or electric fields, such as microwave ovens or refrigerators.

The declaration of conformity according to Directive 2014/53 / EU  
can be found on the website:  
<https://atonyx.cz/content/50-prohlaseni-o-shode> Importer: Atonyx  
sro Harlacherova 3319/4, Praha 10, 10600 IČ: 10796304 DIČ:  
CZ10796304